

Alarm System Transmitter FM4

HIGHLIGHTS

- Additional module for all keyboard-controlled alarm systems
- No installation of driver or additional software necessary
- Plug & Play
- No additional power supply required, power supply via USB
- Extensive equipment: lanyard (neckband with security opening), USB-connecting lead, Velcro tape for fixture (e.g. tables)
- Build-in USB-Hub for connecting mouse or keyboard, if no USB connector available
- Works with every key combination
- Wireless radio remote control for initiation of the alarm system
- Approved and recommended by the Federal Employment Agency Germany and Cordaware



GENERAL

- 2 years of guarantee
- Long battery runtime (approx. 5 years)
- Flexible expandable
- Developed and produced in Germany
- CE-certificated
- Individual leasing offers
- Competence trainings for handling FM4 concerning emergency relief / self-protection are optionally bookable

Alarm system transmitter FM4

Model	0100002
USB ports	1 x plug + 1 x connector
Service voltage	5V over USB
Range	10m to 15m in cleared area
Components	USB-receiver box (grey), radio remote control (red)
Frequency	433 MHZ
CE marking	Yes
Security	Only the programmed key combination will be transmitted. A misuse of the FM4 through hacker attacks is excluded.
Controls	Triggering key (grey) on remote control
Coding	Transmitter and receiver are aligned. The system only works as pre-defined set.
Compatible Emergency Call System	keyboard-bound alarm system - Cordaware (bestinformed Alarm Edition)
Available keyboard combination	All
Equipment	USB connecting lead (2m), neckband with security opening, 20 mm width, red with velcro tape self-retaining, operations manual
Voltage supply	4,40 – 5,50 V DC via USB port
Power input	Max. 0,5 W / 0,1 A
Temperature	+5° C to +45°C
Casing measures W x H x D cm	Receiver box: 8,5 x 3,2 x 6,5, Transmitter: 6,3 x 3,0 x 4,0
Weight	Receiver box: 64g, Transmitter: 26g

Technical Data